

Light patch Main Stage



Venue: Nobel

Adress: Lange Scheistraat 11, 2312CR Leiden

Production: +31 071 303 16 55

General: +31 071 303 16 66

Website: www.nobel.nl

Nobel – Light specifications: Main Stage – September 2026

www.nobel.nl

ADDRESS & CONTACT DETAILS

Artist Entrance	Lange Scheistraat 11, 2312CR Leiden	
Loadingdock	Lammermarkt 43A,	2312CM Leiden
Public Entrance	Marktsteeg 4-8,	2312CS Leiden
Phone	+31 (0) 71 303 16 55	Production
	+31 (0) 71 303 16 66	General
Email	info@nobel.nl	
Advancing	productie@nobel.nl	
Technical Advancing	max@nobel.nl	
Capacity	800 (with balcony)	
Internet		
Wi-Fi SSID	Nobel Artist	
Wi-Fi Password	Blackice2025!	

LOAD IN/OUT

Dimensions of our loading dock:

Length	18 meter
Width	2,8 meter
Height	4,1 meter

Loading dock level: Flat push of approximately 20 meters to the Main Stage

The width of the doorway from loading dock trough the Main Stage is 2,38 meter and the height is 2,68 meter.

Our loading dock is equipped with a lift (unfortunately it's not working).

Dimension of our lift:

Length	2,2 meter
Width	2,2 meter
Max. height	1,2 meter
Weight limit	3.000 kg

In the venue hall we also have a lift. This can be used for audio/lightning consoles

Local tech crew

Standard crew includes:

- 1x Stagemanager (also a loader)
- 1x FOH engineer
- 1x MON engineer
- 1x Light engineer
- 1x Stagehand (1 for load in, 1 for load out)

Extra stagehands available for additional price, arrange with producten in advance

Nobel – Light specifications: Main Stage – September 2026

www.nobel.nl

Light Specifications

Console: GrandMA3 Full-Size
Node: 1x ELC Node8 GBX Slave
3x ELC dmxLAN Switch

sACN
Node: 192.168.0.101
GrandMA3: 192.168.0.1
Guest Desk: 192.168.0.2

Stage fixtures

Spots 18x Ayrton Diablo-s
Washes 12x Ayrton Zonda 3 FX
Side Light 6x Robe 300 (3 per side)
Stroboscope 8x Chauvet Strike M
Blinders 24x Chauvet Strike Array 1
FX 3x Showtec Led Octrostrip set MKII (On request)

Hall Fixtures

Spots 10x Ayrton Diablo-s
Ledbeam 10x Robe 100

First balcony

Ledbeam 8x Robe 100 (4 per side)
FX 12x Cameo Rootbar SMD

Stage Data

CAT 2x Cat6A (1x SL, 1x SR)
5x Cat6A (1x FOH, 2x Light balcony, 2x video control room)
DMX 6x DMX in (1x FOH, 2x Light balcony, 2x video control room)
4x DMX (1x SL, 1x SR)

Smoke

Haze 1x Look Unique 2.1
1x Swefog K1 hazer
Fog 1x Rosco Vapour

DMX PATCH (PER FIXTURES)

Universe 1 (House light)

Universe 1	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Ground Light Venue	1	501	1 Channel Count	
Nr. 2	Bar	1	502	1 Channel Count	
Nr. 3	Ground Floor Balcony Ceilling	1	503	1 Channel Count	
Nr. 4	Video Control Room	1	504	1 Channel Count	
Nr. 5	First Floor Balcony Ceilling	1	505	1 Channel Count	
Nr. 6	Second Floor Bar	1	506	1 Channel Count	
Nr. 7	Second Floor Ceilling	1	507	1 Channel Count	
Nr. 1	Generic RGB	1	1	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 2	Generic RGB	1	5	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 3	Generic RGB	1	9	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 4	Generic RGB	1	13	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 5	Generic RGB	1	17	Generic RGB - 3 Channel	Hall Stairs, RGB Strip

Diablo-S (Ayrton)

Universe 2	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Ayrton Diablo-S	2	157	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr. 2	Ayrton Diablo-S	2	193	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr. 3	Ayrton Diablo-S	2	229	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr. 4	Ayrton Diablo-S	2	265	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr. 5	Ayrton Diablo-S	2	301	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr. 6	Ayrton Diablo-S	2	337	Standard Mode - 36 Channel Count	LX 1 Upstage
Universe 4	Fixture	DMX Line	Adress	Mode	Location
Nr. 7	Ayrton Diablo-S	4	157	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr. 8	Ayrton Diablo-S	4	193	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr. 9	Ayrton Diablo-S	4	229	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr. 10	Ayrton Diablo-S	4	265	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr. 11	Ayrton Diablo-S	4	301	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr. 12	Ayrton Diablo-S	4	337	Standard Mode - 36 Channel Count	LX 2 Midstage
Universe 6	Fixture	DMX Line	Adress	Mode	Location
Nr. 13	Ayrton Diablo-S	6	157	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr. 14	Ayrton Diablo-S	6	193	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr. 15	Ayrton Diablo-S	6	229	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr. 16	Ayrton Diablo-S	6	265	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr. 17	Ayrton Diablo-S	6	301	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr. 18	Ayrton Diablo-S	6	337	Standard Mode - 36 Channel Count	LX 3 Downstage
Universe 8	Fixture	DMX Line	Adress	Mode	Location
Nr. 19	Ayrton Diablo-S	8	1	Standard Mode - 36 Channel Count	Front Truss (LX 6)
Nr. 20	Ayrton Diablo-S	8	37	Standard Mode - 36 Channel Count	Front Truss (LX 6)
Nr. 21	Ayrton Diablo-S	8	73	Standard Mode - 36 Channel Count	Front Truss (LX 6)
Nr. 22	Ayrton Diablo-S	8	109	Standard Mode - 36 Channel Count	Front Truss (LX 6)
Nr. 23	Ayrton Diablo-S	8	145	Standard Mode - 36 Channel Count	Front Truss (LX 6)
Nr. 24	Ayrton Diablo-S	8	181	Standard Mode - 36 Channel Count	Front Truss (LX 6)
Nr. 25	Ayrton Diablo-S	8	217	Standard Mode - 36 Channel Count	Front Truss (LX 5)
Nr. 26	Ayrton Diablo-S	8	253	Standard Mode - 36 Channel Count	Front Truss (LX 5)
Nr. 27	Ayrton Diablo-S	8	289	Standard Mode - 36 Channel Count	Front Truss (LX 5)
Nr. 28	Ayrton Diablo-S	8	325	Standard Mode - 36 Channel Count	Front Truss (LX 5)

Zonda 3FX (Ayrton)

Universe 2	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Ayrton Zonda 3 FX	2	1	Basic Mode - 26 Channel Count	LX 1 Upstage
Nr. 2	Ayrton Zonda 3 FX	2	27	Basic Mode - 26 Channel Count	LX 1 Upstage
Nr. 3	Ayrton Zonda 3 FX	2	53	Basic Mode - 26 Channel Count	LX 1 Upstage
Nr. 4	Ayrton Zonda 3 FX	2	79	Basic Mode - 26 Channel Count	LX 1 Upstage
Nr. 5	Ayrton Zonda 3 FX	2	105	Basic Mode - 26 Channel Count	LX 1 Upstage
Nr. 6	Ayrton Zonda 3 FX	2	131	Basic Mode - 26 Channel Count	LX 1 Upstage
Universe 4	Fixture	DMX Line	Adress	Mode	Location
Nr. 7	Ayrton Zonda 3 FX	4	1	Basic Mode - 26 Channel Count	LX 2 Midstage
Nr. 8	Ayrton Zonda 3 FX	4	27	Basic Mode - 26 Channel Count	LX 2 Midstage
Nr. 9	Ayrton Zonda 3 FX	4	53	Basic Mode - 26 Channel Count	LX 2 Midstage
Nr. 10	Ayrton Zonda 3 FX	4	79	Basic Mode - 26 Channel Count	LX 2 Midstage
Nr. 11	Ayrton Zonda 3 FX	4	105	Basic Mode - 26 Channel Count	LX 2 Midstage
Nr. 12	Ayrton Zonda 3 FX	4	131	Basic Mode - 26 Channel Count	LX 2 Midstage

300 Ledwash (Robe)

Universe 1	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Robin 300 Ledwash	1	101	Mode 2 - 21 Channel Count	Side Stage R
Nr. 2	Robin 300 Ledwash	1	122	Mode 2 - 21 Channel Count	Side Stage R
Nr. 3	Robin 300 Ledwash	1	143	Mode 2 - 21 Channel Count	Side Stage R
Nr. 4	Robin 300 Ledwash	1	164	Mode 2 - 21 Channel Count	Side Stage L
Nr. 5	Robin 300 Ledwash	1	185	Mode 2 - 21 Channel Count	Side Stage L
Nr. 6	Robin 300 Ledwash	1	206	Mode 2 - 21 Channel Count	Side Stage L
(On Request)	Fixture	DMX Line	Adress	Mode	Location
Nr. 7	Robin 300 Ledwash	(On Request)		Mode 2 - 21 Channel Count	Floor (On Request)
Nr. 8	Robin 300 Ledwash	(On Request)		Mode 2 - 21 Channel Count	Floor (On Request)
Nr. 9	Robin 300 Ledwash	(On Request)		Mode 2 - 21 Channel Count	Floor (On Request)
Nr.10	Robin 300 Ledwash	(On Request)		Mode 2 - 21 Channel Count	Floor (On Request)
Nr.11	Robin 300 Ledwash	(On Request)		Mode 2 - 21 Channel Count	Floor (On Request)
Nr.12	Robin 300 Ledwash	(On Request)		Mode 2 - 21 Channel Count	Floor (On Request)

Color Strike M (Chauvet)

Universe 3	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Chauvet Color Strike M	3	27	97 Channel Mode	LX 1 Upstage
Nr. 2	Chauvet Color Strike M	3	124	97 Channel Mode	LX 1 Upstage
Nr. 3	Chauvet Color Strike M	3	221	97 Channel Mode	LX 1 Upstage
Universe 5	Fixture	DMX Line	Adress	Mode	Location
Nr. 4	Chauvet Color Strike M	5	27	97 Channel Mode	LX 2 Midstage
Nr. 5	Chauvet Color Strike M	5	124	97 Channel Mode	LX 2 Midstage
Universe 7	Fixture	DMX Line	Adress	Mode	Location
Nr. 6	Chauvet Color Strike M	7	27	97 Channel Mode	LX 3 Downstage
Nr. 7	Chauvet Color Strike M	7	124	97 Channel Mode	LX 3 Downstage
Nr. 8	Chauvet Color Strike M	7	221	97 Channel Mode	LX 3 Downstage

Strike Array 1 (Chauvet)

Universe 3	Fixture	Dmx Line	Adress	Mode	Location
Nr.1	Chauvet Strike Array 1	3	1	Mode 8Pod - 26CH	LX 1 Upstage
Universe 5	Fixture	DMX Line	Adress	Mode	Location
Nr.2	Chauvet Strike Array 1	5	1	Mode 8Pod - 26CH	LX 2 Midstage
Universe 7	Fixture	DMX Line	Adress	Mode	Location
Nr.3	Chauvet Strike Array 1	7	1	Mode 8Pod - 26CH	LX 3 Downstage

Hazer

Universe 16	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Unique 2.1 Hazer	16	510	2 Channel Fixture	Floor