



## *Light patch Nobel*



## General info

**Venue:** Nobel

**Artist Entrance:** Lange Scheistraat 11, 2312CR

**Loadingdock:** Lammermarkt 43A, 2312CM

**Public Entrance:** Marktsteeg 4-8, 2312CS

**Phone:**

- +31 (0) 71 303 1655
- +31 (0) 71 303 1666

**Website:** [www.nobel.nl](http://www.nobel.nl)

**Capacity:** 800

---

Nobel – Main Stage September 2023

**Desk:**

- 1x Ma-Lightning GrandMA2 Light
- 1x Ma-Lightning GrandMA2 Fader Wing

**Artnet**

- ELC Node 8> IP 2.0.
- GrandMA 2> IP 2.0.
- Guest Desk> IP 2.0.

Line A

Line B

Line C

Line D

Line E

Line F

Line G

Line H

**Stage – Conventional**

- 8x Par64 ACL Set
- 4-Lite Blinder 2,2 kW

**Stage – Intelligent**

- 18x Ayrton Diablo-S (6 on floor, on request)
- 42x Robe Leadbeam 100 (6 on floor, on request)
- 7x Martin Atomic 3000 Strobe (1 on floor, on request)
- 3x Showtec LED Octostrips Set MKII (on request)

**Stage – Data**

- 2x Cat6A stage (1x StageLeft - 1x StageRight)
- 5x Cat6A (1x FoH – 2x Light Balcony – 2x Video Control Room)
- 6x DMX in (1x FoH – 2x Light Balcony – 2x Video Control Room)
- 4x DMX in (2x StageLeft – 2x StageRight)
- 

**Front – Intelligent/Conventional**

- 6x Ayrton Diablo-S
- 2x Selecon SPX Zoom 25° - 50° Profile
- 8ADB Fresnel F101 13° - 59°

**Smoke**

- 2x Swefog K1 (Water Based)
- 2x Rosco Vapour (Oil Based)



## DMX-PATCH

### Universe 1 (Line A)

Universe 1	Fixture	DMX Line	Adress	Mode	Location
Nr.1	ACL	1	21	1 Channel Dimmer	LX 1 Upstage
Nr.2	ACL	1	22	1 Channel Dimmer	LX 1 Upstage
Nr.3	ACL	1	23	1 Channel Dimmer	LX 1 Upstage
Nr.4	ACL	1	31	1 Channel Dimmer	LX 2 MidStage
Nr.5	ACL	1	32	1 Channel Dimmer	LX 2 MidStage
Nr.6	ACL	1	33	1 Channel Dimmer	LX 2 MidStage
Nr.7	ACL	1	47	1 Channel Dimmer	LX 3 Downstage
Nr.8	ACL	1	48	1 Channel Dimmer	LX 3 Downstage
Nr. 1	Blinder (4-Lite)	1	45	1 Channel Dimmer	LX 3 Downstage
Nr. 2	Blinder (4-Lite)	1	29	1 Channel Dimmer	LX 2 MidStage
Nr. 3	Blinder (4-Lite)	1	30	1 Channel Dimmer	LX 2 MidStage
Nr. 4	Blinder (4-Lite)	1	46	1 Channel Dimmer	LX 3 Downstage
Nr. 1	Robin 300 Ledwash	1	101	Mode 2 - 21 Channel Count	Side Stage R
Nr. 2	Robin 300 Ledwash	1	122	Mode 2 - 21 Channel Count	Side Stage R
Nr. 3	Robin 300 Ledwash	1	143	Mode 2 - 21 Channel Count	Side Stage R
Nr. 4	Robin 300 Ledwash	1	164	Mode 2 - 21 Channel Count	Side Stage L
Nr. 5	Robin 300 Ledwash	1	185	Mode 2 - 21 Channel Count	Side Stage L
Nr. 6	Robin 300 Ledwash	1	206	Mode 2 - 21 Channel Count	Side Stage L
Nr. 1	Ground Light Venue	1	501		
Nr. 2	Bar	1	502		
Nr. 3	Ground Floor Balcony Ceilling	1	503		
Nr. 4	Video Control Room	1	504		
Nr. 5	First Floor Balcony Ceilling	1	505		
Nr. 6	Second Floor Bar	1	506		
Nr. 7	Second Floor Ceilling	1	507		
Nr. 1	Generic RGB	1	1	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 2	Generic RGB	1	5	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 3	Generic RGB	1	9	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 4	Generic RGB	1	13	Generic RGB - 3 Channel	Hall Stairs, RGB Strip
Nr. 5	Generic RGB	1	17	Generic RGB - 3 Channel	Hall Stairs, RGB Strip



## Universe 2 (Line B)

Universe 2	Fixture	DMX Line	Adress	Mode	Location
Nr.1	Robin LedBeam 100	2	1	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.2	Robin LedBeam 100	2	20	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.3	Robin LedBeam 100	2	39	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.4	Robin LedBeam 100	2	58	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.5	Robin LedBeam 100	2	77	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.6	Robin LedBeam 100	2	96	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.7	Robin LedBeam 100	2	115	Mode 2- 19 Channel Count	LX 1 Upstage
Nr.8	Robin LedBeam 100	2	134	Mode 2- 19 Channel Count	LX 1 Upstage
<b> </b>					
Nr.1	Ayrton Diablo-S	2	153	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr.2	Ayrton Diablo-S	2	189	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr.3	Ayrton Diablo-S	2	225	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr.4	Ayrton Diablo-S	2	261	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr.5	Ayrton Diablo-S	2	297	Standard Mode - 36 Channel Count	LX 1 Upstage
Nr.6	Ayrton Diablo-S	2	333	Standard Mode - 36 Channel Count	LX 1 Upstage
<b> </b>					
Nr.1	Martin Atomic 3000	2	369	4 Channel Mode	LX 1 Upstage
Nr.2	Martin Atomic 3000	2	373	4 Channel Mode	LX 1 Upstage
Nr.3	Martin Atomic 3000	2	377	4 Channel Mode	LX 1 Upstage



## Universe 3 (Line C)

Universe 3	Fixture	DMX Line	Adress	Mode	Location
Nr.1	Robin LedBeam 100	3	1	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.2	Robin LedBeam 100	3	20	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.3	Robin LedBeam 100	3	39	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.4	Robin LedBeam 100	3	58	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.5	Robin LedBeam 100	3	77	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.6	Robin LedBeam 100	3	96	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.7	Robin LedBeam 100	3	115	Mode 2- 19 Channel Count	LX 2 Midstage
Nr.8	Robin LedBeam 100	3	134	Mode 2- 19 Channel Count	LX 2 Midstage
<b> </b>					
Nr 1	Ayrton Diablo-S	3	153	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr 2	Ayrton Diablo-S	3	189	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr 3	Ayrton Diablo-S	3	225	Standard Mode - 36 Channel Count	LX 2 Midstage
Nr 4	Ayrton Diablo-S	3	261	Standard Mode - 36 Channel Count	LX 2 Midstage
<b> </b>					
Nr 1	Martin Atomic 3000	3	381	4 Channel Mode	LX 2 Midstage
Nr 2	Martin Atomic 3001	3	385	5 Channel Mode	LX 2 Midstage



## Universe 4 (Line D)

Universe 4	Fixture	DMX Line	Adress	Mode	Location
Nr.1	Robin LedBeam 100	4	1	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.2	Robin LedBeam 100	4	20	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.3	Robin LedBeam 100	4	39	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.4	Robin LedBeam 100	4	58	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.5	Robin LedBeam 100	4	77	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.6	Robin LedBeam 100	4	96	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.7	Robin LedBeam 100	4	115	Mode 2- 19 Channel Count	LX 3 Downstage
Nr.8	Robin LedBeam 100	4	134	Mode 2- 19 Channel Count	LX 3 Downstage
Nr 1	Ayrton Diablo-S	4	153	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr 2	Ayrton Diablo-S	4	189	Standard Mode - 36 Channel Count	LX 3 Downstage
Nr 1	Martin Atomic 3000	4	225	4 Channel Mode	LX 3 Downstage



## Universe 5 (Line E)

Universe 5	Fixture	DMX Line	Address	Mode	Location
Nr. 1	Robin LedBeam 300	5	1	Mode 2 - 21 Channel Count	Front Truss
Nr. 2	Robin LedBeam 300	5	22	Mode 2 - 21 Channel Count	Front Truss
Nr. 3	Robin LedBeam 300	5	43	Mode 2 - 21 Channel Count	Front Truss
Nr. 4	Robin LedBeam 300	5	64	Mode 2 - 21 Channel Count	Front Truss
Nr. 5	Robin LedBeam 300	5	85	Mode 2 - 21 Channel Count	Front Truss
Nr. 6	Robin LedBeam 300	5	106	Mode 2 - 21 Channel Count	Front Truss
Nr. 1	Ayrton Diablo-S	5	127	Standard Mode - 36 Channel Count	Front Truss
Nr. 2	Ayrton Diablo-S	5	163	Standard Mode - 36 Channel Count	Front Truss
Nr. 3	Ayrton Diablo-S	5	199	Standard Mode - 36 Channel Count	Front Truss
Nr. 4	Ayrton Diablo-S	5	235	Standard Mode - 36 Channel Count	Front Truss
Nr. 5	Ayrton Diablo-S	5	271	Standard Mode - 36 Channel Count	Front Truss
Nr. 6	Ayrton Diablo-S	5	307	Standard Mode - 36 Channel Count	Front Truss



## Universe 6 (Line F)

Universe 6	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Swefog K1	6	510	2 Channel Fixture	Floor
Nr. 2	Swefog K1	6	510	2 Channel Fixture	Floor
Nr.1	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.2	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.3	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.4	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.5	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.6	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.7	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.8	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.9	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.10	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.11	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.12	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.13	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.14	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.15	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.16	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.17	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)
Nr.18	Robin LedBeam 100	6		Mode 2- 19 Channel Count	Floor (On Request)





Nr.1	Ayrton Diablo-S	6		Standard Mode - 36 Channel Count	Floor (On Request)
Nr.2	Ayrton Diablo-S	6		Standard Mode - 36 Channel Count	Floor (On Request)
Nr.3	Ayrton Diablo-S	6		Standard Mode - 36 Channel Count	Floor (On Request)
Nr.4	Ayrton Diablo-S	6		Standard Mode - 36 Channel Count	Floor (On Request)
Nr.5	Ayrton Diablo-S	6		Standard Mode - 36 Channel Count	Floor (On Request)
Nr.6	Ayrton Diablo-S	6		Standard Mode - 36 Channel Count	Floor (On Request)
Nr. 1	Martin Atomic 3000	6		4 Channel Mode	Floor (On Request)

***Universe 7 (Line G) = Free***

***Universe 8 (Line H) = Free***