



Light patch Club Stage



Lange Scheistraat 11
2312 CR Leiden
+31 71 303 16 55 (Production)/+31 71 303 16 66 (General)
www.nobel.nl
Updated at 4th of September 2026



ADDRESS & CONTACT DETAILS

Artist Entrance	Lange scheistraat 11, 2312CR Leiden
Loadingdock	Lammermarkt 43A, 2312CM Leiden
Public Entrance	Marktsteeg 4-8, 2312CS Leiden
Phone	+31 (0) 71 303 1655 (Production) +31 (0) 71 303 1666 (General)
Email	info@nobel.nl
Advancing	productie@nobel.nl
Technical	Max@nobel.nl
Website	www.nobel.nl
Capacity	200 (with light balcony)

INTERNET

Wi-Fi SSID	Nobel Artist
Wi-Fi Password	Blackice2025!

LOAD IN/OUT

Dimensions of our loading dock

Length:	18 meter
Width:	2,80 meter
Height:	4,10 meter

Loading dock level, flat push of approximately 20m to the Main stage.

The width of the doorway from loading dock trough main stage is 2,38 m and the height is 2,68 m

Our loading dock is equipped with a lift.

Dimension of our lift:

Length	2,2 meter
Width	2,2 meter
Max. height	1,20 meter
Weight limit	3.000 Kg

The width of the doorway from loading dock trough club stage is 2,38 m and the height is 2,68 m

LOCAL TECH CREW

Standard crew includes:

- 1x Stagemanager (also a loader)
- 1x FOH engineer
- 1x Light engineer
- 1x Stagehand (1 for load in, 1 for load out)

Extra stagehands available for additional price – arrange with production in advance



Desk: GrandMA 2 Light + Wing

sACN:

- **Node:** IP 192.168.0.101
- **GrandMA 2:** IP 192.168.0.1
- **Avolites Arena:** IP 192.168.0.2
- **Guest Desk:** IP 192.168.0.3

Stage Conventional:

- 6x Par64 ACL Set
- 4-Lite Blinder 2,2 kW

Stage Intelligent:

- 6x Robe DLX Spot
- 18x Robe LedBeam 100 (Stage)
- 12x Robe Ledbeam 100 (Hall)
- 6x Robe Light4ce
- 1x Martin Atomic 3000 Strobe (1 on floor, on request)
- 3x Showtec Led Octostrips Set MKII (on request)

Stage Data:

- 1x Cat6A Backstage to Baclony
- 1x Cat6A FOH to Backstage
- 2x DMX Stage to Balcony

Smoke:

- 2x Swefog IntellaHazer Duramaxx (Water Based)



DMX Patch (per universe)

Universe 1

Universe 1	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Robin Ledbeam 100	1	1	Mode 2, 19 Channel Count	LX 1 Downstage
Nr. 2	Robin Ledbeam 100	1	20	Mode 2, 19 Channel Count	LX 1 Downstage
Nr. 3	Robin Ledbeam 100	1	39	Mode 2, 19 Channel Count	LX 1 Downstage
Nr. 4	Robin Ledbeam 100	1	58	Mode 2, 19 Channel Count	LX 1 Downstage
Nr. 5	Robin Ledbeam 100	1	77	Mode 2, 19 Channel Count	LX 1 Downstage
Nr. 6	Robin Ledbeam 100	1	96	Mode 2, 19 Channel Count	LX 1 Downstage
Nr. 1	Robin DLX Spot	1	115	Mode 2, 25 Channel Count	LX 1 Downstage
Nr. 2	Robin DLX Spot	1	140	Mode 2, 25 Channel Count	LX 1 Downstage
Nr. 3	Robin DLX Spot	1	165	Mode 2, 25 Channel Count	LX 1 Downstage
Nr. 4	Robin DLX Spot	1	190	Mode 2, 25 Channel Count	LX 1 Downstage
Nr. 1	Robe LedForce7 RGBW	1	221	RGBW, 6 Channel	Side LX 1 SR
Nr. 2	Robe LedForce7 RGBW	1	227	RGBW, 6 Channel	Side LX 1 SL
Nr. 1	Martin Atomic 3000	1	215	4 Channel Count	LX 1 Downstage

Universe 2

Universe 2	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Robin Ledbeam 100	2	1	Mode 2, 19 Channel Count	LX 2 Midstage
Nr. 2	Robin Ledbeam 100	2	20	Mode 2, 19 Channel Count	LX 2 Midstage
Nr. 3	Robin Ledbeam 100	2	39	Mode 2, 19 Channel Count	LX 2 Midstage
Nr. 4	Robin Ledbeam 100	2	58	Mode 2, 19 Channel Count	LX 2 Midstage
Nr. 5	Robin Ledbeam 100	2	77	Mode 2, 19 Channel Count	LX 2 Midstage
Nr. 6	Robin Ledbeam 100	2	96	Mode 2, 19 Channel Count	LX 2 Midstage
Nr. 1	Robin DLX Spot	2	115	Mode 2, 25 Channel Count	LX 2 Midstage
Nr. 2	Robin DLX Spot	2	140	Mode 2, 25 Channel Count	LX 2 Midstage
Nr. 1	Robe LedForce7 RGBW	2	221	RGBW, 6 Channel	Side LX 2 SR
Nr. 2	Robe LedForce7 RGBW	2	227	RGBW, 6 Channel	Side LX 2 SL



Universe 3

Universe 3	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Robin Ledbeam 100	3	1	Mode 2, 19 Channel Count	LX 3 Upstage
Nr. 2	Robin Ledbeam 100	3	20	Mode 2, 19 Channel Count	LX 3 Upstage
Nr. 3	Robin Ledbeam 100	3	39	Mode 2, 19 Channel Count	LX 3 Upstage
Nr. 4	Robin Ledbeam 100	3	58	Mode 2, 19 Channel Count	LX 3 Upstage
Nr. 5	Robin Ledbeam 100	3	77	Mode 2, 19 Channel Count	LX 3 Upstage
Nr. 6	Robin Ledbeam 100	3	96	Mode 2, 19 Channel Count	LX 3 Upstage
Nr. 1	Robe LedForce7 RGBW	3	221	RGBW, 6 Channel	Side LX 3 SR
Nr. 2	Robe LedForce7 RGBW	3	227	RGBW, 6 Channel	Side LX 3 SL
Nr. 1	Blind Chauvet Strike Array 4	3	115	4 Ch Mode / Or Patch 4 dim channels	LX 3 Upstage
Nr. 2	Blind Chauvet Strike Array 4	3	119	4 Ch Mode / Or Patch 4 dim channels	LX 3 Upstage



Universe 4

Universe 4	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Robe LedForce7 RGBW	4	1	RGBW, 6 Channel	Hall
Nr. 2	Robe LedForce7 RGBW	4	7	RGBW, 6 Channel	Hall
Nr. 3	Robe LedForce7 RGBW	4	13	RGBW, 6 Channel	Hall
Nr. 4	Robe LedForce7 RGBW	4	19	RGBW, 6 Channel	Hall
Nr. 5	Robe LedForce7 RGBW	4	25	RGBW, 6 Channel	Hall
Nr. 6	Robe LedForce7 RGBW	4	31	RGBW, 6 Channel	Hall
Nr. 7	Robe LedForce7 RGBW	4	37	RGBW, 6 Channel	Hall
Nr. 8	Robe LedForce7 RGBW	4	43	RGBW, 6 Channel	Hall
Nr. 1	Fresnel	4	49	1 Channel Count	Front
Nr. 2	Fresnel	4	50	1 Channel Count	Front
Nr. 3	Fresnel	4	51	1 Channel Count	Front
Nr. 4	Fresnel	4	52	1 Channel Count	Front
Nr. 5	Profile	4	53	1 Channel Count	Front
Nr. 1	Robin Ledbeam 100	4	201	Mode 2, 19 Channel Count	Hall (Row 1)
Nr. 2	Robin Ledbeam 100	4	220	Mode 2, 19 Channel Count	Hall (Row 1)
Nr. 3	Robin Ledbeam 100	4	239	Mode 2, 19 Channel Count	Hall (Row 1)
Nr. 4	Robin Ledbeam 100	4	258	Mode 2, 19 Channel Count	Hall (Row 1)
Nr. 5	Robin Ledbeam 100	4	277	Mode 2, 19 Channel Count	Hall (Row 1)
Nr. 6	Robin Ledbeam 100	4	296	Mode 2, 19 Channel Count	Hall (Row 1)
Nr. 7	Robin Ledbeam 100	4	315	Mode 2, 19 Channel Count	Hall (Row 2)
Nr. 8	Robin Ledbeam 100	4	334	Mode 2, 19 Channel Count	Hall (Row 2)
Nr. 9	Robin Ledbeam 100	4	353	Mode 2, 19 Channel Count	Hall (Row 2)
Nr. 10	Robin Ledbeam 100	4	372	Mode 2, 19 Channel Count	Hall (Row 2)
Nr. 11	Robin Ledbeam 100	4	391	Mode 2, 19 Channel Count	Hall (Row 2)
Nr. 12	Robin Ledbeam 100	4	410	Mode 2, 19 Channel Count	Hall (Row 2)

Universe 5

Universe 5	Fixture	DMX Line	Adress	Mode	Location
Nr. 1	Look Unique 2.1 hazer	5	510	2 Channel Count	Balcony
Nr. 1	Power Spot 3 Q5	5	1	Mode 3 (9ch)	Under Balcony
Nr. 2	Power Spot 3 Q5	5	10	Mode 3 (9ch)	Under Balcony
Nr. 3	Power Spot 3 Q5	5	19	Mode 3 (9ch)	Under Balcony
Nr. 4	Power Spot 3 Q5	5	28	Mode 3 (9ch)	Under Balcony
Nr. 5	Power Spot 3 Q5	5	37	Mode 3 (9ch)	Under Balcony
Nr. 6	Power Spot 3 Q5	5	46	Mode 3 (9ch)	Under Balcony